Pobrano z mamadecor.pl

LAURA ASHLEY

IL1736

VIENNA CRYSTAL FLUSH CEILING FITTING

INSTALLATION INSTRUCTIONS

These instructions are provided for your safety.
Please read carefully before commencing work and retain for future reference.

SAFETY INFORMATION

* If you are in any doubt consult a person competent to give advice on the installation of electrical equipment.
* This fitting should be fitted in accordance with IEE Wiring Regulations and the Building Regulations
* To prevent electrocution switch off at the mains supply before installing or maintaining this fitting. Ensure other persons cannot restore the electricity supply without your knowledge.
* To avoid damage to concealed wiring during installation, establish the direction of the supply cable before drilling fixing holes.
* This fitting is Class I = and should be fitted to a lighting supply (with earth) protected by a 5 amp fuse or equivalent circuit breaker.
* Always be sure to use the correct type and wattage of bulbs as indicated on the fitting. Never exceed the wattage stated.
* When changing the bulb, always switch off at the mains and allow the old bulb to cool down before handling. Dispose of used bulbs carefully.
* This fitting is designed for use with self-shielded tungsten halogen lamps only =

INSTALLATION

1. Ensure the house electricity supply is off at the fuse board.
2. If you are fitting this product in place of an existing one, you may find that there are more than 3 sets of cables connected. If there are loop in cables that are not connected to the light these must be terminated in a separate terminal block not connected to the fitting. Before removing existing fitting, carefully note position of each set of cables
3. **Do not remove protective packaging from crystals while installing fitting.**
4. Remove mounting bracket from fitting by undoing retaining screws then using as a template, mark and then drill the fixing holes in the ceiling. Ensure that the holes are drilled into a joist or other suitable mounting and not just the plaster.
5. Fix the mounting bracket to ceiling using suitable fixings. **Take care not to damage wiring.** j
6. Weight of the fitting must be supported whilst you make the make electrical connections as follows: k

   Connect the supply live (normally brown or red) to fitting live (marked “L”) on the terminal block.
   Connect the supply neutral (normally blue or black) to fitting neutral (marked “N”) on the terminal block.
   Connect the earth (normally green/yellow or unsheathed) to terminal block marked ‘ ‘on the fitting.
   Ensure electrical connections are tight and no loose strands of wire are left out of the connector block.
7. Attach the fitting to the mounting bracket using the retaining screws removed earlier. l Take care not to trap wires in the process.
8. Fit the bulb type and wattage as indicated on the fitting. m **The wattage indicated must not be exceeded.** Use only self shielded bulbs Do not touch halogen bulbs with bare hands as this will shorten their lives.
9. Remove all the packaging from the crystals.
10. Switch on the electricity supply at the fuse board.

GENERAL INFORMATION

This fitting is designed for internal use only and must be fitted to a DRY SURFACE as any dampness in plaster or paint can damage the finish. **Do not use polish or abrasive cleaner - just a soft dry cloth.**

LUSTRE CRISTAL VIENNA

Pobrano z mamadecor.pl

LAURA ASHLEY

IL1736

INSTRUCTIONS D'INSTALLATION

Ces instructions sont fournies pour votre s curit
Veuillez les lire attentivement avant de commencer travailler et les conse rver pour r f rence future

INFORMATIONS DE S CURIT

* En cas de doute, consultez une personne comp tente pour obtenir des conseils relatifs installation d' quipements lectriq ues.
* Ce lustre doit tre install conform ment aux R glementations de c blage et aux R glementations du b timent de l'IEE
* Pour viter tout risque d'lectrocution, coupez l'alimentation secteur avant d'installer ou d'entretenir ce lustre. Assurez-vous que personne ne pourra r tablir l'alimentation votre insu.
* Pour viter les dommages des fils dissimul s pendant l'installation, v rifiez la direction du c ble d'alimentation avant depercer les orifices de fixation.
* Cet quipement fait partie de la Classe 1 = et doit tre raccord une prise secteur (av ec mise la terr e) prot g par un fusible de 5 amp res ou un coupe-circuit quivalent.
* Veillez toujours utiliser des ampoules de type et de puissance correctes comme indiqu sur le lustre. Ne d passez jamais la puissance recommand
* Lors du remplacement d'une ampoule, coupez toujours l'alimentation secteur et laissez refroidir l'ancienne ampoule avant de la manipuler. Jetez les ampoules us s avec prudence
* Ce lustre est con pour tre utilis uniquement avec des lampes halog nes filament de tungstne blind

INSTALLATION

11. Assurez-vous que l'alimentation lectrique de votre domicile est coup au niveau du disjoncteur.
12. Avant de retirer la rosace existante, notez attentivement la position de chaque s rie de fils. S'il y a des boucles dans les fils qui ne sont pas raccord au luminaire, il convient de les terminer dans un bornier distinct non raccord au luminaire.
13. **Veillez ne pas desembeller les cristals avant d'installation.**
14. Retirez le support de montage du luminaire en d vissant les vis de fixation. En utilisant le support comme mod le, marquez, puis percez les orifices de fixation dans le plafond. Assurez-vous que les orifices sont perc dans une solive ou un autre montage appropri et pas simplement dans le pl tre.
15. Fixez le support de montage au plafond l'aide de fixations appropri es. **Veillez ne pas endommager les fils.** j
16. Le poids du lustre doit tre soutenu pendant que vous effectuez les branchements lectriques. : k

    Branchez le fil d'alimentation directe (normalement marron ou rouge) la prise alimentation du lustre (portant la lettre « L ») du bornier.
    Branchez le fil d'alimentation neutre (normalement bleu ou noir) la prise neutre du lust re (portant la lettre « N ») du bornier.
    Branchez le fil de mise la terre (normalement vert/jaune ou non gain la prise de terre (marqu « ») du bornier.

    REMARQUE : Assurez-vous que les branchements lectriques sont bien serr et qu'aucune longueur de fil ne d as se du bornier. .
17. Placez le luminaire contre le support de montage et alignez les orifices. Fixez en place l'aide des vis retir es pr c demment . l **Veillez ne pas endommager les fils.**
18. Installez les ampoules : respectez le type et la tension mentionn sur le luminaire. **La puissance indiqu ne doit pas e d asser** Utilisez uniquement des ampoules auto-prot g es. **Ne touchez pas les ampoules halog nes mains nues, car cela raccourcirait leur dur e de vie.**
19. Enlevez l'emballage du cristal.
20. Rebranchez l'alimentation au niveau du disjoncteur

INFORMATIONS G N RALES

Ce lustre est destin une installation int rieur uniquement et doit tre fix sur une SURFACE SECHE, car toute trace d'humidit dans le pl tre ou la peinture p ourrait endommager la finition.

Ne pas utiliser de vernis ni de d tergent abrasif, simplement un chiffon sec et doux .