Pobrano z mamadecor.pl

IL313







Instructions for Outdoor wall brackets with two screws holding on ďidô
For Example:

These instructions are provided for your safety.
Please read them carefully before commencing work and retain them for future reference.

This fitting has an IP rating of IP43 and is suitable for outdoor use when connected as below.

SAFETY INFORMATION

* If you are in any doubt consult a person competent to give advice on the installation of electrical equipment.
* Before installation and servicing disconnect the electricity supply at the fuse board.
* To avoid damage to concealed wiring during installation, establish the direction of the supply cable before drilling fixing holes.
* This fitting should be fitted to a lighting supply protected by a 5 amp fuse or equivalent circuit breaker.
* Always be sure to use the correct type and wattage of bulbs as indicated on the fitting. Dispose of old bulbs carefully.

INSTALLATION

Note: This fitting has a 3 year guarantee against corrosion. This fitting should only be installed in normal non aggressive atmospheric locations to prevent corrosion. Aggressive environments to be avoided include locations by the sea, polluted atmospheres or near heating flue outlets.

1. Ensure the house electricity supply is off at the fuse board.
2. If removing an existing fitting, first note down all wiring connections.



3. Unscrew nuts from front of backplate.
Small round rubber washers will be found underneath.
Reserve these carefully for replacement later, as they will form a seal around the screw and prevent corrosion. Remove mounting bracket from fitting and fix firmly to the wall. (Make sure that screws that go through fitting are level or fitting will not be straight when fixed to bracket.)


4. Unscrew four screws holding cover onto box.



5. Unclip connector block from inside box.



6. Push small screwdriver through soft grommet in back of box.



7. Feed supply cable from house supply through hole in soft grommet which will form a seal around the cable
8. The weight of the fitting must be supported whilst you make the electrical connections.
Make all electrical connections through the connector block.
Connect the live (brown) wire of the wall light to the supply live wire normally red.
Connect the neutral (blue) wire of the wall light to the supply neutral wire normally black.
9. Ensure electrical connections are tight and no loose strands of wire are left out of the connector block.
10. Replace cover on box with 4 screws.
11. Fix fitting to wall by threading backplate onto screws in fixing bracket and holding in place with washers and nuts.
12. To fit bulb: Unscrew 2 screws holding on lid and remove lid.. Fit the bulb, type and wattage as indicated on the fitting. **The wattage indicated must not be exceeded.** Replace lid on fitting.
13. Switch on the electricity supply at the fuse board.

Pobrano z mamadecor.pl

IL313



GENERAL INFORMATION

This fitting is designed for external use, it must be fitted to a DRY FINISH as any dampness in concrete, wood stain, paint and etc can damage finish. **Do not use polish or abrasive cleaner - just a soft slightly damp cloth.**

¢2 ℕŜ∃λăüŜℕ è2dzℕ LJℕ2ŘdzŎû ₮2ℕ l·y´ŜËüŜyŘŜŘ ₮ΛØŜπèŜl·ℕ ø l·ℕJℕl·yűèΣ LJfŜl·äŜ Ô2Y´LJfŜüŜ üKŜ ăλY´LJfŜ ₮2ℕY´ l·ú

õ̃ õ̃ õ̃ ΦŘl·ℕJfλ∃Küλy∃ΦŎ2Φõ̃ ⟅κõ̃ l·ℕJℕJl·yűõ̃

¸2dzΩff yŜŜŘ ű2 ₮λff λy´ûKŜ ŘŜűl·λfă 2₮ ûKŜ LJℕ2ŘdzŎûΣ ûKŜ ℕŜűl·λfŜℕ è2dz LJdzℕŎKl·ăŜŘ λû ₮ℕ2YΣ l·yŘ l·fă2 ûKŜ λ̨ãűl·ffŜℕ l·yŘ ûKŜ λyãűl·ffl·ûλ2y¶ tfŜl·äŜ l·fă2 dzLJf2l·Ř l· ŎfŜl·ℕ Ô2LJè 2₮ ûKŜ 2ℕλ∃λYl·f LJdzℕŎKl·äŜ λyØ2λŎŜ 2ℕ ℕŜŎŜλLJű ű2 Ô2Y´LJfŜüŜ ûKλă ℕŜ∃λăúℕl·üλ2y¶

¦ YY ŘĮℕℕ [λ∃KűλyE [űŘΣ ² λfŘYŜℕŜ w2l·ŘΣ. l·yõdzℕèΣ hË2yΣ h · mc oW½

LℕŜfl·yŘ ƨ 9¦Y 5l·ℕ [λ∃KűλyE LℕŜfl·yŘ [λY´λűŜŘΣ {dzλűŜ o ov ϕ2dzãŜΣ mc CdzℕÎŜ w2l·ŘΣ {l·yŘè₮2ℕŘ LyŘdzăúℕλl·f 9ăűl·üŜΣ 5dzōfλy´o o