Pobrano z mamadecor.pl

LAURA ASHLEY

IL1736

VIENNA CRYSTAL FLUSH CEILING FITTING

INSTALLATION INSTRUCTIONS

These instructions are provided for your safety.
Please read carefully before commencing work and retain for future reference.

SAFETY INFORMATION

* If you are in any doubt consult a person competent to give advice on the installation of electrical equipment.
* This fitting should be fitted in accordance with IEE Wiring Regulations and the Building Regulations
* To prevent electrocution switch off at the mains supply before installing or maintaining this fitting. Ensure other persons cannot restore the electricity supply without your knowledge.
* To avoid damage to concealed wiring during installation, establish the direction of the supply cable before drilling fixing holes.
* This fitting is Class I = and should be fitted to a lighting supply (with earth) protected by a 5 amp fuse or equivalent circuit breaker.
* Always be sure to use the correct type and wattage of bulbs as indicated on the fitting. Never exceed the wattage stated.
* When changing the bulb, always switch off at the mains and allow the old bulb to cool down before handling. Dispose of used bulbs carefully.
* This fitting is designed for use with self-shielded tungsten halogen lamps only =

INSTALLATION

1. Ensure the house electricity supply is off at the fuse board.
2. If you are fitting this product in place of an existing one, you may find that there are more than 3 sets of cables connected. If there are loop in cables that are not connected to the light these must be terminated in a separate terminal block not connected to the fitting. Before removing existing fitting, carefully note position of each set of cables
3. **Do not remove protective packaging from crystals while installing fitting.**
4. Remove mounting bracket from fitting by undoing retaining screws then using as a template, mark and then drill the fixing holes in the ceiling. Ensure that the holes are drilled into a joist or other suitable mounting and not just the plaster.
5. Fix the mounting bracket to ceiling using suitable fixings. **Take care not to damage wiring.** j
6. Weight of the fitting must be supported whilst you make the make electrical connections as follows: k

   Connect the supply live (normally brown or red) to fitting live (marked ñLò) on the terminal block.
   Connect the supply neutral (normally blue or black) to fitting neutral (marked ñNò) on the terminal block.
   Connect the earth (normally green/yellow or unsheathed) to terminal block marked d óon the fitting.
   Ensure electrical connections are tight and no loose strands of wire are left out of the connector block.
7. Attach the fitting to the mounting bracket using the retaining screws removed earlier. l Take care not to trap wires in the process.
8. Fit the bulb type and wattage as indicated on the fitting. m **The wattage indicated must not be exceeded.** Use only self shielded bulbs Do not touch halogen bulbs with bare hands as this will shorten their lives.
9. Remove all the packaging from the crystals.
10. Switch on the electricity supply at the fuse board.

GENERAL INFORMATION

This fitting is designed for internal use only and must be fitted to a DRY SURFACE as any dampness in plaster or paint can damage the finish. **Do not use polish or abrasive cleaner - just a soft dry cloth.**

Issue 1 07/08

Pobrano z mamadecor.pl

LAURA ASHLEY

IL1736

LUSTRE CRISTAL VIENNA
INSTRUCTIONS DôINSTALLATION

Ces instructions sont fournies pour votre s¿urit¿
Veuillez les lire attentivement avant de commencer ¿travailler et les conse rver pour r¿f¿rence future

INFORMATIONS DE S¿URIT¿

* En cas de doute, consultez une personne comp®tente pour obtenir des conseils relatifs ¨ lôinstallation dôquipements ®lectriques.
* Ce lustre doit ¿tre install¿conform¿ment aux R¿glementations de c¿blage et aux R¿glementations du b¿timent de l'IEE
* Pour ®viter tout risque dô®lectrocution, coupez lôalimentation secteur avant dôinstaller ou dôentretenir ce lustre. Assurez-vous que personne ne pourra r®tablir lôalimentation ¨ votre insu.
* Pour ®viter les dommages des fils dissimul®s pendant lôinstallation, v®rifiez la direction du c©ble dôalimentation avant depercer les orifices de fixation.
* Cet ¿quipement fait partie de la Classe 1 = [redacted] et doit ¿tre raccord¿une prise secteur (av ec mise ¿la terr e) prot¿¿par un fusible de 5 amp¿es ou un coupe -circuit ¿quivalent.
* Veillez toujours ¿utiliser des ampoules de type et de puissance correctes comme indiqu¿sur le lustre. Ne d¿passez jamais la puissance recommand¿
* Lors du remplacement dôune ampoule, coupez toujours l'alimentation secteur et laissez refroidir l'ancienne ampoule avant de la manipuler. Jetez les ampoules us¿s avec prudence
* Ce lustre est conu¿pour ¿tre utilis¿uniquement avec des lampes halog¿es ¿ filament de tungst¿e blind¿ = [redacted]

INSTALLATION

11. Assurez-vous que lôalimentation ®lectrique de votre domicile est coup¿au niveau du disjoncteur.
12. Avant de retirer la rosace existante, notez attentivement la position de chaque s¿rie de fils. Sôil y a des boucles dans les fils qui ne sont pas raccord¿au luminaire, il convient de les terminer dans un bornier distinct non raccord¿au luminaire.
13. **Veillez ¿ ne pas desembeller les cristals avant dôinstallation.**
14. Retirez le support de montage du luminaire en d¿vissant les vis de fixation. En utilisant le support comme mod¿e, marquez, puis percez les orifices de fixation dans le plafond. Assurez-vous que les orifices sont perc¿dans une solive ou un autre montage appropri¿et pas simplement dans le pl¿re.
15. Fixez le support de montage au plafond ¨ lôaide de fixations appropri¿es. **Veillez ¿ne pas endommager les fils.** j
16. Le poids du lustre doit ¿tre soutenu pendant que vous effectuez les branchements ¿ectriques. : k

    Branchez le fil dôalimentation directe (normalement marron ou rouge) ¿la prise alimentation du lustre (portant la lettre « L ») du bornier.
    Branchez le fil dôalimentation neutre (normalement bleu ou noir) ¿la prise neutre du lust re (portant la lettre « N ») du bornier.

    [redacted]

    Branchez le fil de mise ¿la terre (normalement vert/jaune ou non gain¿¿la prise de terre (marqu¿« [redacted] ») du bornier.

    REMARQUE : Assurez-vous que les branchements ®lectriques sont bien serr®s et quôaucune longueur de fil ne d®passe du bornier. .
17. Placez le luminaire contre le support de montage et alignez les orifices. Fixez en place ¨ lôaide des vis retir®es pr¿¿emment . l **Veillez ¿ne pas endommager les fils.**
18. Installez les ampoules : respectez le type et la tension mentionn¿sur le luminaire. **La puissance indiqu¿ne doit pas ¿tre d¿pass¿** Utilisez uniquement des ampoules auto-prot¿¿s. [redacted] **Ne touchez pas les ampoules halog¿es ¿mains nues, car cela raccourcirait leur dur¿de vie.**
19. Enlevez lôemballage du cristal.
20. Rebranchez lôalimentation au niveau du disjoncteur

INFORMATIONS G¿¿RALES

Ce lustre est destin®¨ une installation ¨ lôint®rieur uniquement et doit °tre fix®sur une SURFACE SÔCHE, car toute trace d'humidit¿dans le pl¿re ou la peinture p ourrait endommager la finition.

Ne pas utiliser de vernis ni de d¿tergent abrasif, simplement un chiffon sec et doux .