Pobrano z mamadecor.pl

INSTALLATION MANUAL

7820

ecostrip | III | DIMMABLE | 90 CRI | CE | RoHS COMPLIANT | DIMMABLE

24V DC | SMD **2216** | **70**LEDs/m | **4,8**W/m | IP**20**

Requires 24V DC driver.
Supplied in 5m roll with double face adhesive tape.

Cut every 10cm (7-LED segment)



one LIGHT

A. CUT:
The LED strip can be cut every 10cm (7-LED segment) at the clearly marked positions. Cut carefully at the desired length by using a sharp pair of scissors.

B. CONNECT:
a) Use 7824 power supply cable to connect the LED strip to the LED driver's output. Ensure that the polarity is correct (red "+", black "-").
b) Connect two pieces of LED strip by using the 7822 connector.

C. INSTALLATION:
Remove the 3M double face adhesive tape from the LED strip gradually during installation and fix into the required position.

A







Warnings:
1. The mounting surface must be clean, dry and free from dust or grease.
2. Make sure that the product is installed properly before connecting to electricity.
3. Do not bend, fold or twist the LED strip.
4. Do not bend to install in corners.
5. Do not put excessive pressure on surface of LED strip.
6. Do not cover LED strip with any materials.
7. Do not install in ambient temperatures below -10°C or exceeding 45°C.
8. Always handle the LED strip with care.
9. The LED strip should not be exposed to direct sunlight.
10. LED strips with different batch numbers may have slight variations in colour consistency (CCT±150K).
11. Maintenance and installation should only be carried out by a professional electrician.