# HALMSTAD 295

Pobrano z mamadecor.pl

Halmstad 295XX0011
23.07.2021 v.11.3
www.norlys.com

## Type of luminaire

| | |
|---|---|
| Type of lumianire | Bollard. |
| Photometric body | Uncovered light, partly covered from the top. |
| Characteristics of the luminaire | Bollard luminaire of stable and durable construction. For lighting private areas and public spaces. |

## General information

| | |
|---|---|
| Materials | Hot-dip galvanized steel. Lens - plastic PMMA in milky color. Silicone gasket. |
| Mounting method | Fixing of the luminaire: 3 holes ø9mm with a diameter of ø65mm every 120 °. |
| Terminal | Connection terminals: max 3x4mm², possibility to connect luminaire in loop max 3x2,5mm². A round wire in the isolation with a diameter of max ø12,5mm. |
| Type of light source | E27 lamp |
| Net / gross weight of luminaire | 7,79kg / 8,44kg |
| Box dimensions [cm] | 15,5x15,5x55 |

## Technical data

| | |
|---|---|
| E27 lamp | QA55 / LED A55..60 |
| Light source wattage | MAX 46W / LED 9W |
| Ta Rated temperature | +25°C |

This product contains light source of energy efficiency class

Possibility to order the luminaire with LED E27 Philips Master LEDbulb 806lm / 8,5W / 2700K (dimmable).

## Accessories sold separately

| | |
|---|---|
| 205ZX0010 | Concreting anchor. |
| 206GA0010 | Ground anchor. |
| 206GA0S10 | Anchoring support. |
| 46999021 | LED E27 lamp. |

## Recommended light sources

| | |
|---|---|
| Osram LED Parathom Classic E27 | Philips Master LEDbulb / Ledbulb Classic E27 |
| Osram ECO PRO Classic 46<=>60W E27 | Philips ECO Classic 42<=>60W E27 |

## Spare parts

| | |
|---|---|
| 06295000 | Lens. |
| 08295000 | Gasket. |

## Files to download

| | |
|---|---|
| Photometric LDT files | Photometric IES files |
| Manual | BIM ArchiCAD |

## Indexes

| Index | Color | RAL |
|---|---|---|
| **295B** | BLACK | 9005 |
| **295GA** | GALVANIZED | - |
| **295GR** | GRAPHITE | 7016 |

Norlys AS
P.B 1014 Hoff, 0218 Oslo
Hovfaret 4B, 0275 Oslo
Norway
+47 24 12 40 11
firmapost@norlys.no

Please read the manual before installing. Due to the dynamic development of lighting technology, additional information is available upon request. LED module must be replaced by a qualified person in accordance with applicable regulations. Condensation, which can occur in luminaires, is a natural phenomenon and does not impair the quality of the luminaire.