ARVIKA 891

Pobrano z mamadecor.pl

Arvika 891XX0011
23.07.2021 v.11.14
www.norlys.com

Type of luminaire

Type of lumianire	Bollard.
Photometric body	Four side light distribution covered from the top.
Characteristics of the luminaire	Bollard luminaire for lighting private areas and public spaces.

General information

Materials	Hot-dip galvanized steel. Hot-dip galvanized and powder-coated steel. Lens - clear polycarbonate, UV stabilized. Silicone gasket.
Mounting method	Fixing of the luminaire: 3 holes ø9mm with a diameter of ø85mm every 120 °. Concreting anchor included to the luminaire.
Terminal	Connection terminals: max 3x4mm², possibility to connect luminaire in loop max 3x2,5mm². A round wire in the isolation with a diameter of max ø12,5mm.
Type of light source	LED module, power supply
Light control	Non-dimmable luminaire
Net / gross weight of luminaire	8,6kg / 9,1kg
Box dimensions [cm]	15x15x91

Technical data

4 LED modules.	Cree JK3030 3000K no.1805004
Driver	OSRAM OT FIT 15/220-240/500 LT2 S
Light source wattage	9,9W
Luminaire wattage	12,7W
Lamp luminous flux	1424lm
Luminaire luminous flux	593lm
Light source efficiency	143,8lm/W
Efficiency of the luminaire	46,7lm/W
ULOR	0%
Color temperature	3000K
Colour consistency (McAdam ellipse)	SDCM3
Colour rendering index CRI	80
Rated life time L70/B50 at 25°C	50 000h
Power Factor luminaire	PF > 0,85
Ta Rated temperature	+25°C

This product contains light sources of energy efficiency class

Inrush current	8A/150µs

Maximum number of luminaires of this type per MCB:

B 10A: 38, **B 16A**: 60

Spare parts

06890003	Lens.
08890000	Gasket.
46999560	LED module.
46999735	Power supply.

Files to download

Photometric LDT files	Photometric IES files
Manual	

Indexes

Index	Color	RAL
891B	BLACK	9005
891GA	GALVANIZED	-

Norlys AS
P.B 1014 Hoff, 0218 Oslo
Hovfaret 4B, 0275 Oslo
Norway
+47 24 12 40 11
firmapost@norlys.no

Please read the manual before installing. Due to the dynamic development of lighting technology, additional information is available upon request. LED module must be replaced by a qualified person in accordance with applicable regulations. Condensation, which can occur in luminaires, is a natural phenomenon and does not impair the quality of the luminaire.